

Features

- One-line backlit LED display
- Displays 10 to 40 alphanumeric characters per line
- Configurable for audible alerts
- Programmable for up to 6 CAP codes
- Wireless data input
- Receives text messages from Tek-CARE® and Tek-ALERT® systems

Description

The SI005 LED Message Sign is a radio paging receiver with a large one-line alphanumeric display. It is designed for use with TekTone's Tek-ALERT Alert Integration Manager, Tek-CARE®120, 160, 400, and 500 Systems.

The SI005 stores up to 24 messages. The messages are deleted after a predetermined length of time. Messages are automatically deleted as new messages arrive (beyond the 24 message limit), with the oldest messages being deleted first.

The SI005 may be configured for annunciation via audible tones. The SI005 has been pre-programmed to receive call information from TekTone systems, and it can be programmed for up to six CAP codes.

Specifications

Dimensions:	6.75"H × 28"L (171 mm × 711 mm)
Weight:	8.4 lbs.
Construction:	LED display board with RF paging circuitry enclosed in a plastic housing
Operating Freq.:	457.550 Mhz
Power Supply:	Input 115 VAC



SI005 LED Messaging Sign

Required Components

NC365B Paging Transmitter

Applicable Systems

Tek-ALERT® Alert Integration Manager
Tek-CARE®120 or 160 Nurse Call System
Tek-CARE®400 P5 or P5+ Nurse Call System
Tek-CARE®400 Nurse Call System
Tek-CARE®500 Wireless Nurse Call System

The LED message sign is an ancillary method of call annunciation, and is not intended to replace the primary annunciation provided by the nurse call system.