

### Features

- Snap-in lens
- Easy bulb replacement
- Flame retardant HIPS 30 plastic panel
- Excellent visibility

### Description

The LI381 Corridor Light provides visual indication of calls when used with a nurse call system, emergency call system, or similar application. Emergency calls are indicated by the rapid flashing of the LI381 Corridor Light associated with the calling station. Normal calls produce a steady illumination.

The standard mounting plate accommodates both models and features an easily removable white flame-retardant translucent polystyrene plastic lens for bulb replacement.

### Required Components

Tek-CARE® NC110, NC150, NC200 or NC300II/III Nurse Call System

Tek-CARE®500 Wireless Emergency Call System with NC50xES-series remote receiver

CM800 Emergency Call System

### Listings



UL® 1069 Listed; UL® File Number E71599.



LI381 Corridor Light

### Specifications

Dimensions:	4.6"H × 4.6"W × 3.3"D (115mm × 115mm × 84mm)
Bulbs:	#1829 28V 70 mA
Power:	24 VDC or VAC, 51 mA
Finish:	White flame retardant translucent polystyrene plastic lens mounted on a flame-retardant (UL®94V-0) plastic panel
Housing:	Fits either standard dual-gang box and ring or single-gang box and ring