

Tek-CARE120 Nurse Call System • Rev. 5 - 2/2025

## **Features**

- CT160 snap-in assembly for use with LI122UN and PM120
- CT160K for stand-alone applications providing same mounting base as the LI and PM's
- Use CT160/K to simplify wiring to room controllers
- Two-wire flying lead and two 8P8C connections
- Convert wiring to use or reuse CAT5e cable to reduce labor and cable cost
- RoHS Compliant



The CT160/K is designed to adapt a connection from a two-wire flying lead to an 8P8C connector which leads to simplified wiring.

The CT160/K allows the installer to convert wiring to use or reuse CAT5e cable (or better) for station wiring for the TC120 Nurse Call Systems.

The CT160 may be connected to PM120 and L1122UN Room Controllers via 3 standoffs provided.

The CT160K is assembled in a plastic housing for standalone mounting.

## **Required Components**

Tek-CARE® 120 Nurse Call System

For Data: NC120 CE Module PM120, LI122UN Room Controllers

For Audio: IR160 Audio Stations





Shown: CT160K (CT160 in mounting hardware)

## **Specifications**

Dimensions 4.8"H  $\times 5.0$ "W  $\times .77$ "D

in housing:  $(122 \text{ mm} \times 127 \text{ mm} \times 20 \text{ mm})$ 

Environment: 0°C-60°C

Construction: PC board with quality electronic com-

ponents mounted on a flame-retardant

(UL® 94V-0) plastic faceplate

Mounting: CT160: Attach to PM120 and LI122UN

Room Controllers

CT160K: Fits standard single- or dual-gang

box with single- or dual-gang ring

Connections: Two-wire flying lead

-and-

CAT5e or better cable using optional 8P8C

connectors

## Listings



RoHS Compliant.