

### Features

- Provides 6 connection points for patient stations, two-button pull-cord stations, and duty stations.
- Easy to wire plug-on pigtailed connectors.
- Lightweight plastic housing protects the electronics.
- Slim package design with modern look

### Description

TekTone's PM120 Room Controller is used in locations where the visual indication of a corridor dome light is not needed. The PM120 provides the interface to a duty station, patient station, and two-button pull-cord stations. The PM120 also provides communication to and from the central equipment module. The PM120 is designed to be installed and mounted where it best fits the system design.

### Listings



The Tek-CARE® 120 and 160 nurse call systems is listed by Underwriters Laboratories, Inc. to the UL® 1069 seventh edition standard for Hospital Signaling and Nurse Call Equipment, the UL® 2560 standard for Emergency Call Systems, and cUL® listed to CSA C22.2 No. 205. UL® File Number E71599.



RoHS Compliant.



PM120 Room Controller

### Specifications

Dimensions: 4.8"H × 5.0"W × .77"D  
(122 mm × 127 mm × 20 mm)

Environment: 0°C–60°C

Housing: Flame-retardant (UL® 94HB) plastic

Mounting: Fits standard one- or two-gang box with one- or two-gang ring

Connections: 6-pin and 8-pin pigtailed connector (harness included)

### Required Components

NC120 or 160 Central Equipment Module  
SF121 Single Patient Station, SF122 Dual Patient Station,  
SF123 Two-Button Pull-Cord Station, and/or SF125 Duty Station

### Optional Components

NC415AV or NC404TS Master Station